

Remote Control Terminal

The remote terminals utilise the same graphical LCD user interface that can be found on the Axis EN series fire panels and are based upon the same advanced, flash based, microprocessor technology.

The Axis EN panels and remote terminals can communicate over the same 2-core network cable.

They feature an integral network interface incorporating a special screen termination to prevent mains frequency earth-loop currents flowing between network nodes.

The Ad-NeT network operates as a true peer-to-peer system with full cross panel reporting, control and cause-and-effect functionality of up to 2000 zones.

All remote terminals incorporate buzzer mute, view, enable/disable and test facilities with dedicated system and navigation keys for simple user control.

The display information is fully programmable by individual zone or sector and can display any combination of fires, faults, pre-alarms or plant alarms. E.g. can display all information in its own sector, but can only show fire signals from other sectors of a building.



Features

- The RCT has additional sector based control keys for Silence, Mute, Resound and Reset, which allows other networked panels to selectively respond to controls as programmed. E.g. on a site with multiple buildings, a user may be allowed to silence and reset fires originating in their own building. Fires originating from other buildings are displayed but cannot be reset.
- Fully on-site programmable via on-board alphanumeric keypad or PC configuration tools.
- View all information from across the network
- By using flash memory and an advanced graphical display the remote terminals can be easily configured to operate in virtually any language, with any character set and allows for the installer's logo and company details to be displayed on the LCD display during normal operation.
- Networked for System Display or Control

Specification

| | |
|----------------------------|---|
| Display | White backlit 240x64 graphical LCD |
| LED Indicators | 2 red (1 x Fire, 1 x Alarm), 1 green (Power) & 3 amber (Fault & System) |
| Keypad | Alpha numeric keypad, navigation keys & on-board buzzer mute facility |
| Controls | System keys for Mute, reset, Silence, Resound |
| Key-Switch Input | Optional level 2 access enable key switch |
| Power Supply Input | 24 VDC, 115mA (/FT: 150mA) operating range 15-30V |
| External Supply Monitoring | Monitored external fault input |
| Number of Fire Zones | 2000 |
| USB/Serial Ports | 1 x USB |

| | |
|-------------------|--|
| Programming | Via on-board keypad or PC running Windows tools |
| Enclosure | Steel IP30 |
| Cable Entry | 20mm knock-outs. 4 x top and 4 x rear |
| Colour | RAL 7035 |
| Size H x W x D mm | Enclosure: 218 x 300 x 42 Back box only (when recessing) 218 x 300 x 30 |
| Metalwork Options | Semi flushing bezel, special finishes including stainless steel & chrome |

Order Codes and Options

| | |
|---------------|---|
| Mx-5020: | (RDT) Remote Display Terminal |
| Mx-5020/FT: | Fault Tolerant version |
| Mxm-521: | Semi-flushing bezel |
| Mxp-518F(F)*: | Access enable key-switch |
| Mxs-028: | Spare peripheral Fault Tolerant network interface |
| (F)* | Add - Fitted |

[Check if this document is up to date](#) | [Give us feedback](#)

Advanced, The Bridges, Balliol Business Park, Newcastle, NE12 8EW, UK T: +44 (0)845 894 7000, E: enquiries@advancedco.com, W: www.advancedco.com

As our policy is one of constant product improvement the right is therefore reserved to modify product specifications without prior notice.