

1 Loop Fire Alarm Control Panel

The Axis EN series control panels are supplied with a single loop driver card, 2 onboard sounder circuits, 20 programmable zonal LEDs with slide-in labels, and 25 system LEDs for information purposes. There are also 4 programmable function buttons with LED indication for confirmation of operation.

The control panel consists of the latest dual flash-based microprocessor technology combined with a high resolution, high contrast, graphical LCD display and tactile keypad providing a simple 'select & click' programming aid for engineer configuration and end user operation.

Powerful cause-and-effect programming coupled with dynamic zoning, and enhanced trace diagnostics makes the panel suitable for a wide range of site applications from small to large complex multi-area systems. Fully programmable on-site via the on-board alphanumeric keypad, or PC-NeT Configuration Software.

An extensive suite of user-friendly Windows based PC software programs has been developed to enhance your experience when using Axis EN series fire panels. The suite incorporates a number of different programmes which include configuration, service, logo and virtual panel tools to allow the flexibility of the equipment to be fully explored.

Simply adding a network card allows the panel to communicate with any other Axis EN fire panel, remote terminal, or network periferal, such as ipGateway™, BMS or graphical interface. The network operates as a true peer-to-peer system and can be configured in a faulttolerant loop or radial format.



Features

- 20 programmable zonal / 25 System LEDs.
- Advanced graphical LCD user interface and support for up to 200 fire zones by default allowing full EN54 compliance without additional hardware.
- Dedicated USB & RS232 Serial Port for direct PC or modem connection.
- Installer friendly Auto-learn, Loop Detection and On-board Scope facility.
- Graphical display configurable for virtually any language.
- Robust removable equipment chassis with plug-in connectors for simple fixing and cable termination.
- Integral P-Bus for system expansion via available option cards.
- Ad-NeT peer-to-peer network with up to 2000 zones
- Approved to EN54 part 2, 4 and 13

Approvals



- EN54-2:1997 +AC:1999 +A1:2006
- EN54-4:1997 +AC:1999 +A1:2002 +A2:2006
- EN 50130-4: 2011+A1:2014
- EN 55032:2015
- EN 62368-1:2014+A11:2017
- EN 62368-1:2020+A11:2020
- EN IEC 63000:2018
- EN 54-13:2017 (Pending)

Specification

| | |
|--------------------------------|---|
| Base technology | Dual flash-based processors with real-time clock, trace diagnostics, programmable languages and character sets |
| Display | White backlit 240 x 64 graphical LCD (5.5 inches x 2.5 inches) |
| LED Indicators | 22 red (1 x Fire, 1 x More Alarms, 20 x Zonal Programmable), 1 green (Power), 13 amber and 12 bi-colour (Fault & System) |
| Controls | Alpha numeric keypad permitting navigation, Reset, Mute, Silence, Resound, Evacuate, and 4 x Programmable push buttons |
| Number of Fire Zones | 2000 (200 per individual panel) |
| Number of Loops | 1 |
| Devices per Loop | Up to 240 |
| Loop Current | 500mA |
| On-Board Sounder Circuits | x 1 Amp programmable |
| On-Board Relays | 2 x 1 Amp 30v AC/DC programmable(10mA, 5v min) - expandable to 4 using Mxp-507 |
| Auxiliary Supply | 1 x 24v 500mA |
| Programmable Input | 1 x monitored programmable input on-board |
| Programmable Key Switch Inputs | 1 x volt free input (standard enc.), 8 x inputs (M, L, D enc.) |
| Total Available Output Current | 3A maximum available for loop current + sounder outputs + auxiliary supply |
| Mains Supply | 200 - 240v 47-63 Hz AC (+10%, -15% tolerance) 1.0A Max |
| Battery Capacity | 24v 4 Ah internal (min), 24v, 7 Ah internal (max), medium enc. (M) - 24v, 12Ah internal (max), large enc. (L) - 24v, 18Ah internal (max), deep enc. (D) - 24v, 45Ah |
| Charger Current | 1A temperature compensated |
| Serial Port | 1 x on-board RS232 connection for PC, modem, IP, or portable printer |
| USB Interface | 1 x USB B type connection for PC communication |
| Programming | On-board keypad or PC running Windows tools |
| Event Log | 5000 event & diagnostic + 500 fire |
| Networking | Optional plug-in network card (Mxp-503 - standard, or Mxp-509 - fault-tolerant) |
| Printer (optional) | On-board (M, L, D enclosures only) |
| Enclosure / Colour | Steel IP30 / RAL7035 |
| Temperature | -5°C to 40°C |
| Metalwork Options | Flushing bezel, battery box, utility enclosure and termination enclosure |

Dimensions and Capacity

| | Dimensions | Cable Entry | Battery Capacity (internal) | |
|-------------------|-----------------|------------------------------|-----------------------------|----------|
| | H x W x D mm | (20mm knockouts) | Min | Max |
| Standard | 345 x 345 x 85 | 13 x top, 8 x rear | 24v 4Ah | 24v 7Ah |
| Medium | 345 x 430 x 120 | 17 x top, 11 x rear | 24v 4Ah | 24v 12Ah |
| Large | 475 x 450 x 120 | 19 x top, 11 x rear | 24v 4Ah | 24v 18Ah |
| Large-Deep | 475 x 450 x 190 | 30 x top, 11 rear & 3 bottom | 24v 4Ah | 24v 45Ah |

Order Codes and Options

| | |
|-------------|---|
| Axis-5101: | Single Loop Panel in Standard Enclosure |
| Axis-5101M: | Single Loop Panel in Medium Sized Enclosure |
| Axis-5101L: | Single Loop Panel in Large Enclosure |
| Axis-5101D: | Single Loop Panel in Large Deep Enclosure |

[Check if this document is up to date](#) | [Give us feedback](#)

Advanced, The Bridges, Balliol Business Park, Newcastle upon Tyne, NE12 8EW, UK **T:** +44 (0)345 894 7000, **E:** enquiries@advancedco.com,
W: www.advancedco.com

As our policy is one of constant product improvement the right is therefore reserved to modify product specifications without prior notice.