

Fibre Optic Converter

Introduction

The Mxp-631 media converters are equipped with a multiple interface circuit that can handle RS-232 or RS-422/485 serial interfaces and multi-mode or single-mode fiber. Mxp-631 converters are used to extend serial transmission up to 5km (Mxp-631-MM with multi-mode fiber) or up to 40km (Mxp-631-SM with single-mode fiber). The Mxp-631 converters can be configured to convert either RS-232 signals, or RS422/485 signals, but not both at the same time.

Automatic Baudrate Detection

The Mxp-631 converters can automatically detect the serial baudrate. This is an extremely convenient feature. Even if a device's baudrate is changed, the signal will still be transmitted through the media converter without any data loss.

Ring Operation

The Mxp-631 converters can be used to connect serial devices to a fiber ring. To form the ring, connect to the Tx port of one Mxp-631 to the Rx port of a neighbouring converter. Once the ring is set up, simply use the DIP switches to configure the Mxp-631 converters for "ring mode". When one node transmits a signal, the signal travels around the ring until it returns back to the transmitting unit, which then blocks the signal. With the Mxp-631, you can set up fiber rings that have a total circumference of up to 100km.

Automatic Data Direction Control (ADCC®)

ADDC® is a patented hardware data flow solution to handle RS-485 data direction control. ADDC® senses and controls RS-485 data direction automatically, making it unnecessary to use the hand shaking signal.

Please note that this way of communication is not EN54 approved.

Features

- Extends RS-232/422/485 transmission up to :
- *40 km with single-mode - Mxp-631-SM
- *5 km with multi-mode - Mxp-631-MM
- Compact size
- Protects against electrical interference and chemical corrosion
- Supports baudrates of 50 bps to 921.6 Kbps
- Wide temperature models available (-40 to 75°C)

Specification

Fiber Connector	SC or ST
Cable Requirements	Single-mode: 8.3/125, 8.7/125, 9/125 or 10/125 Multi-mode: 50/125, 62.5/125 or 100/140
Transmission Distance	Single-mode: 40km Multi-mode: 5km
Wavelength	Single-mode: 1310nm

Multi-mode: 850nm

Tx Output

Single-mode: > -5dBm

Multi-mode: > -5dBm

Rx Sensitivity

Single-mode: -25 dBm

Multi-mode: 20 dBm

Point-to-point Transmission

Half-duplex or Full duplex

Ring Transmission

Half-duplex

RS-232/422/485 Side:**Connector**

Terminal Block

RS-232 Signals

Tx, Rx, GND

RS-422 Signals

TxD+, TxD-, RxD+, RxD-, GND

RS-485-4w Signals

TxD+, TxD-, RxD+, RxD-, GND

RS-485-2w Signals

Data+, Data-, GND

Physical Characteristics:**Housing**

Aluminium

Dimensions

Without ears: 67 x 100 x 22mm (2.64 x 3.94 x 0.87in)

With ears: 90 x 100 x 22mm (3.54 x 3.94 x 0.87in)

Environmental Limits:**Operating Temperature**

Standard Models: 0 to 60°C (32 to 140°F)

Wide Temp Models: -40 to 75°C (-40 to 167°F)

Operating Humidity

5 to 95% RH

Storage Temperature

-40 to 75°C (-40 to 167°F)

Power Requirements:**Input Voltage**

12 to 48 VDC

Power Consumption

140ma @ 12V

Power Line Protection

2 Kv Burst (EFT), EN61000-4-4

2 Kv Surge, EN61000-4-5

Voltage Reversal Protection

Protects against V+/V- reversal

Over Current Protection

1.1A (protects against two signals shorted together)

Regulatory Approvals:**FCC**

Part 15 Subclass B

UL/CUL

UL60950-1

EMI

EN55022 1998, Class B

EMS

EN61000-4-2 (ESD), Criteria A, Level 3

EN61000-4-3 (RS), Criteria A, Level 2
EN61000-4-4 (EFT), Criteria A, Level 2
EN61000-4-5 (SURGE), Criteria A, Level 3
EN61000-4-6 (CS), Criteria A, Level 2
EN61000-4-8 (SFMF), Criteria A, Level 1

Warranty:

Warranty Period 3 years

Details See www.advancedco.com

Order Codes and Options

Mxp-631-MM:	RS-232/422/485 to multi-mode optical fiber media converter
Mxp-631-SM:	RS-232/422/485 to single-mode optical fiber media converter
Mxp-542:	24VDC - 24VDC Convertor / Isolator (required if powering Mxp-631 from an Axis EN control panel)

[Check if this document is up to date](#) | [Give us feedback](#)

Advanced, The Bridges, Balliol Business Park, Newcastle upon Tyne, NE12 8EW, UK **T:** +44 (0)345 894 7000, **E:** enquiries@advancedco.com,
W: www.advancedco.com

As our policy is one of constant product improvement the right is therefore reserved to modify product specifications without prior notice.