

The ipGateway connects to an existing Ad-Net fire panel network and provides a gateway to the network from any remote location over the internet.

By gathering real time information from the fire network it gives a visual indication of the state of the fire panel network through a standard web browser.

The state of each device on the network is displayed in a clear and concise manner.

Interaction with the fire network is also available, providing the functionality to enable/disable zones, enable/disable devices, reset, mute, and silence/resound sounders on the network.

The ipGateway can also be configured to react to events on the network by sending emails to configured recipients.

Applications / Limitations

Provides remote access to devices on an Ad-Net/Ad-Net+ Network.

Configurable event email notification.

Features

- Remote access to Ad- Net fire network using a standard web browser
- Password protected
- Multiple user permissions
- Event notification via email
- Configurable over the internet
- No proprietary software required

Specification

| | |
|------------------------|--|
| Supply Voltage input | 18-28V DC |
| Supply Current | 48mA(/FT: 86mA) at 24V DC |
| Enclosure H x W x D mm | IP30: 218 x 300 x 45 |
| Weight | 2 Kg |
| Knockouts | 4 top, 4 bottom, 4 bottom rear |
| Temperature range | -5°C to 50°C / 95% humidity (non-condensing) |
| Serial Interface | Isolated RS 232 interface |
| Fault Input | Monitor input for power supply fault output |
| Indications | On-board LED indicators for heartbeat, network transmit/receive, RS232 transmit/receive, LAN Activity, LAN Connectivity, LAN Run 7 |
| Ethernet Interface | 10Base-T, RJ45 |

Order Codes and Options

| | |
|----------------|--|
| MXP-554: | ipGateway (Card Only) Standard Network |
| MXP-554/FT: | ipGateway (Card Only) Fault Tolerant Network |
| MXP-554-BX: | ipGateway (Boxed) Standard Network |
| MXP-554-BX/FT: | ipGateway (Boxed) Fault Tolerant Network |

Compatibility

The ipGateway can be connected to any Ad-Net/Ad-Net+ network system and Local Area Network. This interface can be configured using PC-NET-003 configuration software v5 onwards, and panel software version 23.02 onwards.

Browsers – Most versions of Internet Explorer and Firefox.

[Check if this document is up to date](#) | [Give us feedback](#)

Advanced, The Bridges, Balliol Business Park, Newcastle upon Tyne, NE12 8EW, UK T: +44 (0)345 894 7000, E: enquiries@advancedco.com,
W: www.advancedco.com

As our policy is one of constant product improvement the right is therefore reserved to modify product specifications without prior notice.