

## Power Supply Units

The Advanced 1.5A, 3.0A and 5.0A power supply units can be used for any fire alarm system which specifies EN54-4 power supply equipment.

Suited for almost any application, the power supply unit/battery charger has been developed using the latest surface mount technology to provide a high efficiency switch mode power supply.

The power supply units are available in fully enclosed construction providing power and fault indication or alternatively in caged versions for mounting into existing enclosures of various sizes to suit different battery capacities.

PSE and charger or PSE only options on the 3.0A and 5.0A versions.

A Serial Link option is provided on the 3.0A and 5.0A versions. Allows reporting of PSE status and voltages / current measurements to compatible control panel / modules.

### Applications

For any fire alarm system which specifies EN54-4 power supplies (e.g. BS5839 code of practice).

These power supply units can be used in any fire alarm installation requiring a 24Volt supply for operation.



### Features

- A range of power supply equipment with power output options to suit most applications.
- Universal AC input on the 3.0A and 5.0A versions
- High efficiency switched mode power supplies
- Compact 1.5A, 3.0A and 5.0A versions

### Specification

Approvals	All power supply units are approved with the requirements of BS EN54-4 1998, EN55022 class B emissions limits & EN60950: 2000 safety standards.
Input Supply	1.5A PSE:220-240V AC, 50/60Hz, fuse T3.15H250 - 3.0A/5.0A PSE:200-240V AC, 50/60Hz, fuse T3.15H250
Output Voltage	Max 28.5V DC, Min 18.5V DC at minimum battery voltage of 19V with mains disconnected
Charger voltage	27.4V DC nominal at 20°C temperature compensated over the range -5°C to +45°C
Output Current	1.5A PSU: 1.0A continuous load, 0.5A battery charge 3.0A PSU: 2.0A continuous load, 1.0A battery charge [3.0A to load if configured for PSU only] 5.0A PSU: 3.0A continuous load, 2.0A battery charge [5.0A to load if configured for PSU only]
Dimensions Boxed H x W x D mm	7Ahr 263 x 246 x 85. 17Ahr 378 x 338 x 110. 38Ahr 410 x 363 x 185.
Environment	Indoor, dry
Fault Output	Volt-free change-over contacts rated 1A @ 30V dc
On Board Indication	Mains Fail, Charger Fail, Battery Open Circuit, Battery Low & Heartbeat

## Order Codes and Options

Mxp-549:	1.5A PSE in 7Ah enclosure
Mxp-550:	3.0A PSE in 17Ah enclosure
Mxp-550/D:	3.0A PSE in 38Ah enclosure
Mxp-551	5.0A PSE in 17Ah enclosure
Mxp-551/D	5.0A PSE in 38Ah enclosure

[Check if this document is up to date](#) | [Give us feedback](#)

Advanced, The Bridges, Balliol Business Park, Newcastle, NE12 8EW, UK T: +44 (0)845 894 7000, E: [enquiries@advancedco.com](mailto:enquiries@advancedco.com), W: [www.advancedco.com](http://www.advancedco.com)

As our policy is one of constant product improvement the right is therefore reserved to modify product specifications without prior notice.