

## 4-Way Programmable Sounder Card

The Programmable 4-Way Sounder Card is an optional peripheral unit that provides four individually programmable, and monitored, sounder output circuits compliant with BSEN54-2: 1998 Clause 7.8.

Up to 16 cards can be connected to a multi-loop panel providing a maximum of 64 additional local sounder outputs. Each output is fully programmable using the powerful dynamic cause-and-effect rules, and all outputs are synchronised.


The unit is available as either a printed circuit card only or as a boxed version with integral 4A power supply.

### Applications / Limitations

EN54-2 compliant sounder outputs.

Can be used with MxPro 4 2, 4 & 8 loop control panels programmed with version 020-02 software, or later, and fitted with base card hardware revision levels 10 (712-1022 MxPro 5 4 loop) and 09 (712-1022-002 MxPro 5 2 loop) or later.

Requires installation of the Peripheral Bus Interface Adaptor card in the panel when using the MxPro 4 series.



### Features

- Each output is 1A rated, and monitored for open and short circuits.
- Each output is individually programmable using the Dynamix cause-and-effects rules.
- All outputs can be synchronised in pulsing modes.
- Up to 16 cards can be connected giving a total of 64 additional outputs.
- Each output may be individually programmed
- Easily configured via PC-NET-003
- 3 year warranty as standard

### Specification

Applicable Standards	BS EN54-2: 1998, BS EN54-4: 1998
Operating Temperature	-5°C to 40°C
Relative Humidity	95% non-condensing (maximum)
PCB Dimensions H x W x D mm	PCB 110 x 86 x 18
PCB Weight	75 grams
Enclosure	Steel, IP30, RAL9002
Enclosure Dimensions H x W x D mm	320 x 345 x 88
Weight	5 kg (excluding batteries)
Knockouts 20mm	7 x top, 2 x bottom
AC Supply	230V AC, 50Hz (+10%, -15%) FUSE T3. 15H250
Standby Battery	2 x 12V, 7AH Sealed lead-acid type (Yuasa recommended)
LED Indications (PCB)	Sounder circuit on, communications TX & RX and heartbeat
LED Indications (Box)	Power and general PSU fault - separate indications of specific PSU fault conditions are available on the PSU.

Outputs (x4)

24VDC 1A

## Order codes and Options

Mxp-034:	4-Way Programmable Sounder Card
Mxp-034-BXP:	4-Way Programmable Sounder Card Boxed with 4A PSU

[Check if this document is up to date](#) | [Give us feedback](#)

Advanced, The Bridges, Balliol Business Park, Newcastle upon Tyne, NE12 8EW, UK **T:** +44 (0)345 894 7000, **E:** [enquiries@advancedco.com](mailto:enquiries@advancedco.com),  
**W:** [www.advancedco.com](http://www.advancedco.com)

As our policy is one of constant product improvement the right is therefore reserved to modify product specifications without prior notice.