

Sounder Mounting Base

Product Information

The sounder mounting base has a wide interior diameter for ease of access to cables and terminals.

The 'E-Z Fit' feature allows you to fit the base screws, place the XPERT 8 mounting base over the screws, slide it into place and tighten the screws. The detector requires a clockwise rotation into the base for fitting.

Additionally the detector can be locked into the base for increased security, by a grub screw using a 1.5mm hexagonal driver.

The XPERT 8 card supplied with the base, has pre-punched pips to remove to set the address.



Features

- Compatible with:
 - EVAC-SNDR/R
 - EVAC-SNDR/W
 - EVAC-SVAD/RW
 - EVAC-SVAD/WW
- Isolated wiper - maintains loop connectivity during temporary removal of devices
- Supplied with XPERT 8 card
- 'E-Z Fit' allows for simple mounting of the detector base after wiring
- Base mark allows for LED detector alignment

Standards and Approvals

- EN IEC 63000:2018 - Hazardous substances
- BS EN 61000-6-3:2007 +A1:2011 - Electromagnetic compatibility
- BS EN 50130-4:2011 +A1:2014 - Electromagnetic compatibility
- EN 15804:2012 +A2:2019 - Environmental product declaration

Order Codes and Options

EVAC-MB/W	Sounder mounting base (White)
EVAC-MB/R	Sounder mounting base (Red)

Specification

Dimensions	100mm diameter x 20mm deep	
Weight	61g	
Materials	Base:	White flame-retardant polycarbonate
	Terminals:	Nickle plated stainless steel

Note: All data is supplied subject to change without notice. Specifications are typical at 24V, +25°C and 50% RH unless otherwise stated.